


INSTRUCTION SHEET  
for: **2PF 959 590-xxx & 2055**




ADR - APPLICATION AND MOUNTING INSTRUCTIONS

ADR 49/00 Front End-Outline Marker Lamp

ADR 49/00 Front Position (Side) Lamp

FRONT END-OUTLINE MARKER LAMP AND FRONT POSITION (SIDE) LAMP

Lens Marking and ADR 13/00 Installation Requirements

This lamp, identified by lens marking A (E24) 02 0054 and the  logo was manufactured to comply with ADR 49/00 Front End-Outline Lamps / Front Position (Side) Lamps.

- A tolerance of +/-3 degrees applies on all mounting details.
- Lamp mounting surface must be vertical to the ground and be square to the vehicle longitudinal axis
- Lamp reference axis can be horizontal or vertical.

Front End-Outline Marker Lamp

- Lamp must be visible between  
Horizontal angle: 0° inwards (parallel with vehicle axis) and 80° outwards  
Vertical angle: 5° above and 20° below the horizontal

Front Position (Side) Lamp

- Lamp must be visible between  
Horizontal angle: 45° inwards and 80° outwards  
Vertical angle: 15° above and below the horizontal

Note: Please refer to ADR 13/00 for more details.

79.0

22.4

16.3

A

(E24)

02 0054

Reference axis

57.5

Mounting surface

16.0


HELLA

Made in New Zealand

44.1

All dimensions in millimetres


LENS IDENTIFICATION NUMBER: A (E24) 02 0054

CATALOGUE NUMBER	ENGINEERING NUMBER	CRN NUMBER	ECE COMPLIANCE NUMBER	ADR 51/00 GLOBE	ADR APPLICABLE
2055	2PF 959 590-40	N/A ECE	A E24 02 0054	N/A LED	ADR 49/00 ECE R 7/01
AMENDMENTS			<div><div>ECE COMPLIANCE VERIFIED</div><div></div></div>	ISSUE DATE:	
08/08	10/08	01/11		10/00	
				959 149-26	

HELLA-New Zealand Limited, Pakuranga

959 149-26 / 04.19

INSTRUCTION SHEET  
for: **2PF 959 590-xxx & 2055**




ADR - APPLICATION AND MOUNTING INSTRUCTIONS

ADR 49/00 Front End-Outline Marker Lamp

ADR 49/00 Front Position (Side) Lamp

FRONT END-OUTLINE MARKER LAMP AND FRONT POSITION (SIDE) LAMP

Lens Marking and ADR 13/00 Installation Requirements

This lamp, identified by lens marking A (E24) 02 0054 and the  logo was manufactured to comply with ADR 49/00 Front End-Outline Lamps / Front Position (Side) Lamps.

- A tolerance of +/-3 degrees applies on all mounting details.
- Lamp mounting surface must be vertical to the ground and be square to the vehicle longitudinal axis
- Lamp reference axis can be horizontal or vertical.

Front End-Outline Marker Lamp

- Lamp must be visible between  
Horizontal angle: 0° inwards (parallel with vehicle axis) and 80° outwards  
Vertical angle: 5° above and 20° below the horizontal

Front Position (Side) Lamp

- Lamp must be visible between  
Horizontal angle: 45° inwards and 80° outwards  
Vertical angle: 15° above and below the horizontal

Note: Please refer to ADR 13/00 for more details.

79.0

22.4

16.3

A

(E24)

02 0054

Reference axis

57.5

Mounting surface

16.0


HELLA

Made in New Zealand

44.1

All dimensions in millimetres


LENS IDENTIFICATION NUMBER: A (E24) 02 0054

CATALOGUE NUMBER	ENGINEERING NUMBER	CRN NUMBER	ECE COMPLIANCE NUMBER	ADR 51/00 GLOBE	ADR APPLICABLE
2055	2PF 959 590-40	N/A ECE	A E24 02 0054	N/A LED	ADR 49/00 ECE R 7/01
AMENDMENTS			<div><div>ECE COMPLIANCE VERIFIED</div><div></div></div>	ISSUE DATE:	
08/08	10/08	01/11		10/00	
				959 149-26	

HELLA-New Zealand Limited, Pakuranga

959 149-26 / 04.19

INSTRUCTION SHEET  
for: **2PF 959 590-xxx & 2055**



Lamp Mounting Instructions

Ensure the lamp is mounted on a flat surface with the gasket provided. The lens may be used as a template for the mounting holes. Mount the lamp and fit screw caps into the mounting hole recesses of the lens.

Note: Lamp is fully sealed and has no serviceable components.  
If it is necessary to remove the screw caps, use a pin.

Wiring Colour Coding

The marker lamp is multi voltage capable allowing full light output between 8 and 28 volts.  
LED lamps are polarity conscious. Reverse polarity will not damage this product but will inhibit its function.  
HELLA recommends wire connections be soldered, and heat shrink tubing applied to seal the joint.


Colour	Connect to	Power Consumption
Black	Earth (-)	-
White (Red Trace)	Positive(+)	0.4 watts @ 12 volts 0.8 watts @ 24 volts

NB: Lamp must be protected by a fuse rated at 2 amperes maximum.

Energy saving recommendation for 24 volt systems

To derive the full benefit of the low power consumption (0.4 watts), HELLA recommends to wire pairs of marker lamps in series.

**FIT AND FORGET - BY DESIGN**



Congratulations, the product you have selected comes from **HELLA** - a world leader in LED lighting design.


Following the launch of the first LED automotive signal lamps in 1990, **HELLA** Design and Innovation continues to set new standards. **HELLA** innovative solutions have been incorporated into millions of lamps, engineered and tested to the most stringent standards, to suit the most demanding environmental conditions.

The cornerstone to the success of our products is our no compromise **Fit and Forget - by Design** philosophy which is incorporated into every step of the product life cycle.

In a world consuming finite resources at an ever faster rate, **Fit and Forget - by Design** is the right environmental choice that also makes perfect economic sense to customers that consider the total life cycle Cost of Ownership.

*For general comments about HELLA's products please contact us on E-mail at [techfeedback@hella.co.nz](mailto:techfeedback@hella.co.nz)*

INSTRUCTION SHEET  
for: **2PF 959 590-xxx & 2055**



Lamp Mounting Instructions

Ensure the lamp is mounted on a flat surface with the gasket provided. The lens may be used as a template for the mounting holes. Mount the lamp and fit screw caps into the mounting hole recesses of the lens.

Note: Lamp is fully sealed and has no serviceable components.  
If it is necessary to remove the screw caps, use a pin.

Wiring Colour Coding

The marker lamp is multi voltage capable allowing full light output between 8 and 28 volts.  
LED lamps are polarity conscious. Reverse polarity will not damage this product but will inhibit its function.  
HELLA recommends wire connections be soldered, and heat shrink tubing applied to seal the joint.


Colour	Connect to	Power Consumption
Black	Earth (-)	-
White (Red Trace)	Positive(+)	0.4 watts @ 12 volts 0.8 watts @ 24 volts

NB: Lamp must be protected by a fuse rated at 2 amperes maximum.

Energy saving recommendation for 24 volt systems

To derive the full benefit of the low power consumption (0.4 watts), HELLA recommends to wire pairs of marker lamps in series.

**FIT AND FORGET - BY DESIGN**



Congratulations, the product you have selected comes from **HELLA** - a world leader in LED lighting design.

Following the launch of the first LED automotive signal lamps in 1990, **HELLA** Design and Innovation continues to set new standards. **HELLA** innovative solutions have been incorporated into millions of lamps, engineered and tested to the most stringent standards, to suit the most demanding environmental conditions.

The cornerstone to the success of our products is our no compromise **Fit and Forget - by Design** philosophy which is incorporated into every step of the product life cycle.

In a world consuming finite resources at an ever faster rate, **Fit and Forget - by Design** is the right environmental choice that also makes perfect economic sense to customers that consider the total life cycle Cost of Ownership.

*For general comments about HELLA's products please contact us on E-mail at [techfeedback@hella.co.nz](mailto:techfeedback@hella.co.nz)*